



Main Features:

1. Compact design for laptop users
2. Cherry MX switches inside
3. Arbitrary programming key-code and LED colors
4. Build in 4 layers for programming
5. PBT DSA profile keycaps with Dye-Sublimated technology
6. Anodized CNC-machined aluminum case (Narrow bezel)
7. Detachable Micro USB cable

Package Content :

1. Keyboard x 1
2. Micro USB Cable x 1
3. Extra Mac & RGBY modifiers keycap

 <http://amazon.com/Vortexgear> or <https://vortexgear.us> 

 <https://amazon.ca/Vortexgear> or <https://vortexgear.ca> 

Keyboard Layout (Default):



1. Switch O.S:

- ❖ Windows: Pn + W
- ❖ Mac: Pn + M
 - Windows interchangeable with Alt
 - F1~F12 please refer to the mac keyboard layout
 - Some keys need to set their own
- ❖ Linux: Pn + L
 - Caps lock interchangeable with L_Ctrl

2. Switch Keyboard Layout:

- a) QWERTY: Fn + Home
- b) COLEMAK: Fn + PgUp
- c) DVORAK: Fn + PgDn



3. Spacebar LEDs instructions:

- a) Left side LED – Switching Layers (Fn + R_shift)
 - i. Red - Layer 1
 - ii. Green - Layer 2
 - iii. Blue - Layer 3
 - iv. None - Default
- b) Right side LED – Switching layout Windows lock
 - i. Red - COLEMAK
 - ii. Green - DVORAK
 - iii. Blue – Windows lock
 - iv. None – QWERTY (Default)

4. Other functions:

- a) Programming steps please refer to POK3R manual [<https://images-na.ssl-images-amazon.com/images/I/81HJ6x12RzL.pdf>]
- b) Reset the current layer key-codes: Fn + R
- c) Reset all layers' key-codes and restore to default: L_Alt + R_Alt
- d) Swap Fn position:

Hit Fn + L_Alt for 3 seconds then select new Fn key location directly

5. RGB Backlit:

Multi-color dynamic Backlighting				
Pn	+	ESC	=	Palette
		1		Single Color - Red
		2		Single Color - Green
		3		Single Color - Blue
		4		Display single color LED mode ¹
		5		Display full color LED mode ²
		9		Custom LED mode 1
		0		Custom LED mode 2
		-_		Display recording 1
		=+		Display recording 2
		X		Brightness down
		V		Brightness up
		<		Light effect speed up
		>		Light effect speed up

RGB LEDs edit descriptions:

The RGB Race 3 has a total of 3 layers to edit the LEDs³.

Step 1. Choose a layer (Fn+<, > or ? key) you want to edit.

Step 2. Press Pn + 9 or 0 to enter the edit mode.

Step 3. Press Pn + 1, 2 and 3 to mix color⁴ **OR** press Pn + ESC⁵ to turn on the palette and select a color you want.

Step 4. Select a key or a row you want to change color. Step 5. Press Pn + 9 or 0 again to exit edit mode. Step 6. Press Pn + - or Pn + = to display the previously saved setting.

¹ Interactive mode, Flash vortex mode, Aurora mode

² Full key light mode, Breath mode, Vortex mode, Rain drop mode.

³ Each layer can be edited in single key (Pn+9) or whole row (Pn+0)

⁴ The color you mixed will show on Pn key

⁵ There are total have 61 kinds of colors on palette.